



F&F Filipowski sp. j
ul. Konstantynowska 79/81
95-200 Pabianice POLAND
tel/fax 48 42 2270971
e-mail: fif@fif.com.pl

AWZ-30

LIGHT DEPENDENT RELAYS hermetic



www.fif.com.pl

F&F products are covered by an 24 months warranty from date of purchase

PURPOSE

Light dependent relay servers to switch -ON the lighting of streets, squares, shop windows, neon lamps etc, at twilight and to switch -OFF afore mentioned lighting at dawn

FUNCTIONING

The relay should be situated at place with permanent access to day light, which, due to its changes of intensity, will cause switching ON and OFF the lighting. The exact time of switching the lighting can be set by potentiometer by the user. Turn in the direction of "half moon" will delay switching-ON, turning in the direction of "sun" will advance switching-ON. The relay is equipped with a delay system, which delays switching ON and OFF the lighting, thus eliminating the influence of accidental disturbances like thunder lightings on the relay functioning.

ASSEMBLY

1. The relay fast upright (connection to down) to the substrate by two screws at place with permanent access to day light, which due to its changes of intensity, will cause switching ON and OFF the lighting.
2. To turn OFF supply.

3. To take OFF the cover.
4. Impref connection wire over the connector and connect it in accordance with marks.
5. By screwdriver set to switching threshold
6. To take ON the cover..


ATTENTION!

In the case of check the power to act the relay, all relay should be securely covered, e.g. by carton or dark mine cloth. Covered just probe "eye", e.g. by finger is insufficient because intensity of day light is very intense and penetrate to fotoresistor by the plastic box and human body.

TECHNICAL DATA

| | |
|---------------------------------------|------------------------------------|
| supply | 230V AC |
| current load | <30A |
| switching threshold (setting range) | 2÷1000Lx |
| switching threshold (factory setting) | aprox. 7Lx |
| hysteresis | 15Lx |
| switching ON delay | 1÷15sec |
| switching OFF delay | 10÷30sec |
| power consumption | 0,56W |
| protection level | IP65 |
| connection | screw terminals 2,5mm ² |
| working temperature | -25÷50°C |
| dimensions | 74×86×35mm |
| fixing | two screws |

WIRING DIAGRAM



A090331