

Soldering Station



Features:

- ESD safe - suitable for work on static-sensitive components
- Three programmable preset temperature buttons
- Easy to read white-on-blue LCD with temperature in °C or °F
- On / Off switch on side of unit
- Includes soldering iron, stand, and sponge
- Additional range of soldering tips available
- New appearance design, big LCD screen, for clear and convenient reading
- PID power control loop with constant temperature set by MCU computer for more precision temperature control
- Imported temperature-resistant materials with long life
- It is convenient that the device adopt three programmable knobs in different condition
- Display the temperature between Fahrenheit and Celsius flexibly, convenient for the type of operators
- Computerized temperature calibration can correct the difference between the actual and display temperature quickly
- Heating element malfunction alert

Apply

Manufacturing production line
On field soldering jobs
Lead-free solder

Specifications:

Input voltage : 220V AC (110 V optional)
Input frequency : 50/60Hz
Maximum power consumption : 60W
Temperature range : 150°C to 450°C
Tip and ground impedance : < 2Ω
Tip and ground potential : < 5mV
Heating element : 2 cores, 60W

Soldering Iron:

Measurement : 240mm × 40mm × 60mm
Gross weight : 0.125Kg
Compatible for : 21-10115 (AT938D)

Part Number Table

Description	Part Number
Soldering Iron, 60W, 220V/110V	AT907-938D
Soldering Station, Digital, ESD, EU	21-10115 EU
Soldering Station, Digital, ESD, UK	21-10115 UK

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Tenma is the registered trademark of the Group. © Premier Farnell plc 2012.

